

# AEGIS 7000<sup>PLUS</sup> SERIES

## MULTI TENANT DEDICATED TELEPHONE ENTRY SYSTEM



- 150-250 tenants and 150-250 access codes
- Local programming via keypad with audio prompts
- 1x16 Electronic Liquid Crystal Display (LCD)
- Non-Volatile memory
- Single Relay
- Support pause dialing from the PBX
- Indoor or outdoor, surface and full-flush mount.
- Brushed Stainless Steel Faceplate

Warranty: 24 months

### SPECIFICATIONS

**POWER INPUT:** 12VAC/40VA (supplied) or 12-VDC/40VA with battery backup charging circuit.

**CURRENT CONSUMPTION:** 500mA idle, 700mA operating.

**OPERATING ENVIRONMENT:** 32°F to 140°F. Heater is required if the temperature is below 32°F.

**NIGHT LIGHT:** Super Bright Light Emitting Diode (LED).

**CONSTRUCTION:** 16 Gauge Cold Rolled Steel back box with enamel finished and Brushed Stainless Steel Faceplate

**MOUNTING:** Surface and full-flush.

**DIMENSIONS:**

Surface 10-13/16" (H) x 8-5/8" (W) x 3-3/4" (D).

Full-flush 10-13/16" (H) x 8-3/8" (W) x 2-7/16" (D)

**MOUNTING RING FULL-FLUSH (FFM7 is included):**

Inside 11-1/8" (H) x 8-11/16" (W) x 2-5/8" (D)

Outside 14-5/16" (H) x 12-1/8" (W)

**SHIPPING WEIGHT:** 11-15 lb approximate.

see quick guide or manual for further specifications

### ORDERING PART

#### Surface Mount

**7150P**

150 tenants 150 access codes

**7250P**

250 tenants 250 access codes

#### Full-flush Mount

**7150FFP**

150 tenants 150 access codes

**7250FFP**

250 tenants 250 access codes

### ACCESSORIES

#### Radio Receiver and Transmitter

**ARFR** Radio Frequency Receiver

**ARFT** Radio Frequency Transmitter

**ARFHT** Radio Frequency Handheld Transmitter

#### Video Package

**UVPC** Color Camera Package

**UVPB** Video Balun for Twisted Pair video transmission

#### Pedestal Mounting Post, Adapter Plate and Mounting Ring

**UPM1S** Standard Single Arm (42"H, 5"x5" base)

**UPM4S** Standard Single Arm (47"H, 5"x5" base)

**UPM1L** Large Single Arm (47"H, 8"x8" base)

**UPM6L** Large Single Arm (64"H, 8"x8" base)

**UPM8L** Large Single Arm (84"H, 8"x8" base)

**UPM2** Double Vertical Arm (44"/84"H, 8"x8"

base)

**UPM5** Double Horizontal Arm (47"H, 8"x8" base)

**UPMDB64** Single Arm Direct Buriel (64"H)

**UPMDB72** Single Arm Direct Buriel (72"H)

**UAP78** Adapter Plate AeGIS 8000P Series

**UPM12E** 12" Expansion Arm use for all UPM

#### Miscellaneous Accessories

**FFM7** Full-flush mounting ring, included w/ system

**USP1** AC and Telephone Surge Protector.

**AHP5** Heater Pad with Thermostat.

**UBAT1** 12VDC 4.5 Ahr backup battery.

**ARIGB8** Rough-in gang box.

**ADIR** Paper Directory with night light

**7SHLD** Sun Shield

**AXIT** Multipurpose push button switch

Specifications subject to change without prior notice

PACH AND COMPANY

Home of Telephone Access Control Systems

AEGIS QUANTUM

Phone: 1-888-678-7224

949-498-2951

www.pach-co.com